



PROGRAMMABLE VIDEO SWITCHING MATRIX

- 32 video inputs and 8 video outputs
- 64 sequences (with 32 steps each)
- 32 alarm inputs
- Windows 95 / NT PC configuration
- Videoloss detector

The SW328 video matrix is a global solution concerning collection and management of images. The matrix is capable of switching 32 video inputs on 8 independent outputs.

The system offers the possibility to activate 64 different synchronized sequences among several monitors, with day, night and holiday cycles.

The matrix provides 32 alarm inputs, 8 relays controlled by events or alarm contacts (alarm groups), alarm reset through keyboard, external contact or automatic timed reset, user friendly configuration through Windows 95 / NT PC.

This product is noteworthy because of the possibility to record the events on a printer, to point out the lack of video signals, and thanks to a competitive price.

A keyboard, equipped by a joystick, controlled by a microprocessor, allows to see directly cameras on which act and control the telemetry and auxiliary functions.



SW328 with DCS3

Dimensions: rack 19" 5HE

Weight: 6,8 Kg

Depth: 250mm

CODE	DESCRIPTION
SW328	Video matrix 32 inputs and 8 outputs

SW328

Video matrix

- inputs: 32
- outputs: 8
- users: 8
- alarm inputs: 32
- video signal: 1Vpp/75Ω
- power supply: 230V~50/60Hz 50W

