

ECOR 8 – 8-channel MPEG-4 digital video recorder



ECOR-8 / ECOR-8 A



ECOR-8 D / ECOR-8 AD

Specifications

Video format: PAL / CCIR

Display format: 1, 4, 6, 9x multiscreen, sequence

Video input: 8 video inputs 1 Vp-p composite PAL, BNC, automatic 75 Ohm termination

Video output:

1 main monitor output, 1 Vp-p at 75 Ohm, BNC

1 main monitor output VGA 800x600, 15-pin Sub-D

Video compression: MPEG-4

Display resolution: 800 x 600

Harddisk storage: 1 x internal 3,5" SATA HDD

Recording resolution: 704 x 576, 704 x 288, 352 x 288

Recording rate: 1 ~ 200 IPS (352 x 288) total

1 ~ 100 IPS (704 x 288) total

1 ~ 50 IPS (704 x 576) total

1 ~ 25 IPS individual setup per channel for normal and event recording (remaining rate to be distributed among remaining channels)

Recording modes: continuous, schedule or event recording

Playback search: via time/date or event, smart search functionality

Video pause: yes

Video loss detection: yes

Motion detection: yes, with configurable detection area and sensitivity

Event log: 10000 log entries

Alarm input: 8 alarm inputs

Alarm output: 1 relay output N.O. / N.C.

Audio: 1 input / 1 output (only ECOR-8 A / ECOR-8 AD)

Setup: on-screen display with graphic user interface (GUI)

Control: USB mouse control, front panel control, optional: IR remote control, network, RS-485 keyboard EKB 500

Timer: built-in real time clock

Title: 16-characters title generator for each camera

Archive: USB 2.0 interface

Built-in DVD-RW drive (only ECOR-8 D / ECOR-8 AD)

Ethernet: RJ45 network connector

RS-232: 9-pin Sub-D

RS-485: 1 x screw terminal connector

Password protection: 3 levels with individual user rights assignment

Power source: 12 V DC, via external power supply 100 ~ 240 V AC

Power consumption: 40 W max.

Ambient temperature: 0°C ~ +40°C

Dimensions: 320 (W) x 50 (H) x 210 (D) mm

Features

- User-friendly graphic user interface (GUI) with easy mouse or front panel operation
- Latest MPEG-4 compression technology with improved picture quality
- individual recording settings for each channel
- data archiving via USB 2.0 port
- programmable motion detection area for each channel
- PTZ control
- Internal DVD-RW drive for easy video export (ECOR-8 D / ECOR-8 AD)
- Audio functionality (ECOR-8 A / ECOR-8 AD)
- Ethernet interface for remote network viewing and controlling
- fast network video transmission through either Internet Explorer (ActiveX application)
- network operation independent from local operation
- optional RS-485 remote control (EKB 500)

Ordering information

| ECOR model number | Description |
|-------------------|--|
| ECOR-8 | 8-channel MPEG-4 DVR with built-in SATA harddisk |
| ECOR-8 D | 8-channel MPEG-4 DVR with built-in SATA harddisk and built-in DVD-RW drive |
| ECOR-8 A | 8-channel MPEG-4 DVR with built-in SATA harddisk and audio function |
| ECOR-8 AD | 8-channel MPEG-4 DVR with built-in SATA harddisk, audio function and built-in DVD-RW drive |